



Outdoor TV mixer

broadband inputs L series

art. 22-055
MIX2L V+4-5



This outdoor TV mixer is ideal to combine the signals of two antennas and distribute them to the TV on a single cable.

This mixer is designed to optimize the reception of DTT signals in the range E05÷E12+E21÷E48, attenuating the 700 MHz band without preventing the proper functioning of the channel E48.

The two inputs are so distributed:

- 1 VHF+4 band input
- 1 band 5 input.

On request it can be provided with the possibility to enable the remote power supply.

Created with calibration on request. When ordering you must specify the last channel of the band 4 and the first of the band 5.

Characteristics

- Shielded housing with screw F-type connectors
- Fixing accessory suitable for masts up to Ø 60 mm included

Code	22-055	
Item	MIX2L V+4-5	
No. of inputs	2	
No. of outputs	1	
Insertion loss	dB ±1	< 3
Inputs isolation	dB	> 20
Dimensions (LxWxH)	mm	77x50x85
Packaging dimensions (LxWxH)	mm	100x90x54
Packaging weight	Kg	0,17
Fit temperature	°C	-10 ÷ +55
Compliant to	EN 55083-2, EN 60065	

Technical data refer to a temperature of 25 °C

Example of application

